

CEEtyp Plugs/couplers with screw terminals



1. Dismantle approx. 50 mm of the cable and strip 10 mm of the wires, then feed the cable through the back part.



2. Connect all conductors according to the cover plate markings, using a screwdriver PZ1.



3. Adjust the back part on the thread of the front part and ...



4. ... turn until both parts lock in place automatically.



5. Finally tighten the cable gland (torque at least 4 Nm) - ready.



6. To disassemble first unscrew the cable gland (a). Then press a screwdriver, blade width 3,0 mm, deeply into the opening slot of the back part. Turn screwdriver clockwise to unlock the parts again.

Connectable lines:

16 A: 1 – 4,0 mm²

32 A: 2,5 – 6 mm²

External cable diameter:

16 A: 7,5 – 18,5 mm (above EN 60309)

32 A: 10 – 22,5 mm (above EN 60309)

Latest version (update): www.walther-werke.de

